

FLYSKY TRANSMITTER & RECEIVER COMPATIBILITY TABLE

2,4GHz RF system					R E C E I V E R																	
					non-AFHDS		AFHDS						AFHDS 2	AFHDS 2A								
Type	No. of channels		3-ch	6-ch	3-ch				6-ch	8-ch	4-ch	3-ch	4-ch	6-ch				8-ch	10-ch			
		Tx / Rx	GR3A	R6A	GR3B	GR3C	GR3E	GR3F	R6B	R9B	iR4	A3	iA4B	A6	iA6	iA6B	X6B	A8S	iA10	iA10B		
AFHDS	wheel	2-ch	GT2	X	X	✓	✓	✓	✓	✓	✓	X	X	X	X	X	X	X	X	X	X	
			GT2B	X	X	✓	✓	✓	✓	✓	✓	✓	X	X	X	X	X	X	X	X	X	X
		3-ch	GT3	1)	1)	2)	2)	2)	2)	2)	2)	2)	X	X	X	X	X	X	X	X	X	X
			GT3B	X	X	✓	✓	✓	✓	✓	3)	3)	X	X	X	X	X	X	X	X	X	X
	stick	2-ch	GT3C	X	X	✓	✓	✓	✓	✓	3)	3)	X	X	X	X	X	X	X	X	X	X
			T2A	X	X	✓	✓	✓	✓	✓	✓	✓	X	X	X	X	X	X	X	X	X	X
		4-ch	T4A	✓	✓	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
			T4B	X	X	✓	✓	✓	✓	✓	✓	✓	X	X	X	X	X	X	X	X	X	X
		6-ch	CT6A	✓	✓	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
			CT6B	X	X	✓	✓	✓	✓	✓	✓	✓	X	X	X	X	X	X	X	X	X	X
		8-ch	T6	X	X	✓	✓	✓	✓	✓	✓	✓	X	X	X	X	X	X	X	X	X	X
			TH9X	1)	1)	2)	2)	2)	2)	2)	2)	2)	X	X	X	X	X	X	X	X	X	X
AFHDS 2	wheel	4-ch	iT4	X	X	4)	4)	4)	4)	4)	4)	✓	X	X	X	X	X	X	X	X	X	
AFHDS 2A	wheel	2-ch	GT2E	X	X	✓	✓	✓	✓	✓	✓	X	✓	✓	✓	✓	✓	?	?	✓	✓	
			GT2G	X	X	✓	✓	✓	✓	✓	✓	✓	X	✓	✓	✓	✓	✓	?	?	✓	✓
			GT2F	X	X	✓	✓	✓	✓	✓	✓	✓	X	✓	✓	✓	✓	✓	?	?	✓	✓
		3-ch	RED i3	X	X	✓	✓	✓	✓	✓	✓	✓	X	✓	✓	✓	✓	✓	?	?	✓	✓
	stick	4-ch	iT4S	X	X	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	?	?	✓	✓
		4-ch	i4	X	X	✓	✓	✓	✓	✓	✓	✓	X	✓	✓	✓	✓	✓	✓	✓	✓	✓
			i4X	X	X	✓	✓	✓	✓	✓	✓	✓	X	✓	✓	✓	✓	✓	✓	✓	✓	✓
		6-ch	i6	X	X	✓	✓	✓	✓	✓	✓	3)	X	✓	✓	✓	✓	✓	✓	3)	3)	3)
			i6X	X	X	✓	✓	✓	✓	✓	✓	✓	X	✓	✓	✓	✓	✓	✓	✓	✓	✓
		10-ch	i6S	X	X	X	X	X	X	X	X	X	X	✓	✓	✓	✓	✓	✓	✓	✓	✓
i10	X		X	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	

✓

compatible

X

not compatible

?

not confirmed

1)

only with FS-TM001 RF module

2)

only with FS-TM002 RF module

3)

all channels available with transmitter firmware hack

4)

only later version with upgraded firmware

